25 mm (1") photomultiplier 9116B series data sheet



1 description

The 9116B is a compact 25mm (1") diameter, end window photomultiplier with a hemispherical window for 2π detection, enhanced green sensitive bialkali photocathode and 6 high gain, high stability, SbCs dynodes of circular focused design for fast timing. The 9116WB is a variant for applications requiring UV sensitivity. The effective photocathode area is approximately twice that of a 25 mm plano-planar type.

2 applications

- · high energy physics studies
- astrophysics

3 features


- compact
- 2π detection
- · fast time response

4 window characteristics

	9116B borosilicate	9116WB UV glass
spectral range (nm)* refractive index (n _d)	295 - 680 1.49	170 - 630 1.48
radio purity content: K (ppm) Th (ppb) U (ppb)	1400 900 1100	8500 30 30

 $^{^{\}star}$ wavelength range over which quantum efficiency excessd % of peak

5 typical spectral response curves




6 characteristics


photocathode: bialkali active diameter quantum efficiency at peak luminous sensitivity with CB filter with CR filter	mm % µA/lm	7	22 (2π) 26 90 11 5	
dynodes: 6CFSbCs anode sensitivity in divider A:				
nom. anode sensitivity max. rated anode sensitivity overall V for nom. A/Im overall V for max. rated A/Im	A/lm A/lm V V		1 5 850 1300	1200
gain at nom. A/lm dark current at 20 °C:	x 10 ⁶		0.01	
dc at nom. A/lm dc at max. rated A/lm pulsed linearity (-5% deviation)	nA nA		0.3 1.5	5
divider A	mA		2	
rate effect (I _a for ∆ g/g=1%):	μA		20	
magnetic field sensitivity: the field for which the output decreases by 50 %				
most sensitive direction	T x 10 ⁻⁴		2.5	
temperature coefficient:	% °C ⁻¹		± 0.5	
timing: multi electron rise time multi electron fwhm transit time delay weight:	ns ns ns g		1.8 3.1 17 15	
maximum ratings:	_			400
anode current cathode current	μA nA			100 30
gain sensitivity temperature V (k-a) ⁽¹⁾	x 10 ⁶ A/lm °C V	-30		0.06 5 60 1800
V (k-d1) V (d-d) ⁽²⁾ ambient pressure (absolute):	V V kPa			400 200 202

 $[\]stackrel{(1)}{\text{subject}}$ to not exceeding max. rated sensitivity $\stackrel{(2)}{\text{subject}}$ to not exceeding max rated V(k-a)

typical voltage gain characteristics




8 voltage divider distribution




Characteristics contained in this data sheet refer to divider A unless stated otherwise.

9 external dimensions mm




10 base configuration (viewed from below)



Our range of B14B sockets, available for this series, includes versions with or without a mounting flange, and with contacts for mounting directly onto printed circuit boards.

11 ordering information

The 9116B meets the specification given in this data sheet. You may order **variants** by adding a suffix to the type number. You may also order **options** by adding a suffix to the type number. You may order product with **specification options** by discussing your requirements with us. If your selection option is for one-off order, then the product will be referred to as 9116A. For a repeat order, **ET Enterprises** will give the product a two digit suffix after the letter B, for example B21. This identifies your specific requirement.



12 voltage dividers

The standard voltage dividers available for all variants of this pmt are tabulated below:

C617A	2R	F	2	 	 				R	R		R
C617B	2R	F	2	 	 				R	2F	2	4R

 $R = 330 \text{ k}\Omega$

ET Enterprises Limited 45 Riverside Way Uxbridge UB8 2YF United Kingdom tel: +44 (0) 1895 200880

tel: +44 (0) 1895 200880 toll free: (800) 399 4557 fax: +44 (0) 1895 270873 fax: (325) 235 2872 e-mail: sales@et-enterprises.com web site: www.et-enterprises.com web site: www.et-enterprises.com

ADIT Electron Tubes 300 Crane Street Sweetwater TX 79556 USA tel: (325) 235 1418 toll free: (800) 399 4557 fax: (325) 235 2872 choose accessories for this pmt on our website

an ISO 9001 and ISO 14001 registered company

The company reserves the right to modify these designs and specifications without notice. Developmental devices are intended for evaluation and no obligation is assumed for future manufacture. While every effort is made to ensure accuracy of published information the company cannot be held responsible for errors or consequences arising therefrom.

